

Description	Zero-Phase Current Transformer	Drawn Date	12/10/11
Part No.	ZT033100PP	Sample No.	2317

Mechanical Dimensions in mm

Mechanical Specifications:
 International Tolerance(mm)

0~3	±0.1
3~6	±0.12
6~10	±0.15
10~18	±0.18
18~30	±0.20
30~50	±0.25
50~80	±0.30
80~120	±0.35

Test Circuit:

Photo:

Description	Zero-Phase Current Transformer	Drawn Date	12/10/11
Part No.	ZT033100PP	Sample No.	2317

Electrical Specifications

Rated Primary Current 50Hz/60Hz(Amp.)	15(30)
Turns ration	Np:Ns=1:1000
D.C.Resistance Max.at 20	54Ω
Rated Output Voltage (mV)	6.0min@Io=10mA, RL=800Ω
Operating temp.	-20 ~65
'Storage temp.	-25 ~85
Dielectric Withstanding Voltage(Hi-pot)	2.5KVrms/1mA/1sec
Insulation Resistance	DC500V/100MΩ min

Mechanical Specifications

CUP	5010GN6-30 M8X(PBT)
Encapsulant	epoxy
Output terminal	2pinΦ0.8
Approx.Weight	3.0g

Standard(s) & Edition Number for this evaluation:

IEEE C57.13 - STANDARD REQUIREMENTS FOR INSTRUMENT TRANSFORMERS - Edition 1 - Issue Date 2008/03/27,

CSA C60044-1 - INSTRUMENT TRANSFORMERS – PART 1: CURRENT TRANSFORMERS - Edition 1 - Issue Date 2007/03/01

CSA C60044-2 - INSTRUMENT TRANSFORMERS – PART 2: INDUCTIVE VOLTAGE TRANSFORMERS - Edition 1 - Issue Date 2007/03/01

ANSI/IEEE C57.13, "Standard Requirements for Instrument Transformers"

CAN3-C13-M83 "Instrument Transformers Certified for Canada - Component



E318452



RoHS COMPLIANT